Jitendra Kumar Verma et al./ Elixir Elec. Engg. 90 (2016) 37735-37737

Available online at www.elixirpublishers.com (Elixir International Journal)

**Electrical Engineering** 



Elixir Elec. Engg. 90 (2016) 37735-37737

# Enhancement of ECG signal by DFT using Fast Fourier Transform (FFT) Algorithm

Jitendra Kumar Verma, Anil Kumar and Arvind Kumar Jaiswal Department of Electronics & Communication Engineering, SSET, SHIATS-DU, Allahabad, India.

# **ARTICLE INFO**

Article history: Received: 3 May 2015; Received in revised form: 8 January 2016; Accepted: 14 January 2016;

### Keywords

ECG, Channel noise, Gaussian function, FFT, Wavelet transform, S-Transform.

# ABSTRACT

A primarily diagnostic tool for cardiovascular diseases ECG, a non invasive technique generally used during acquisition and transportation. Noises like channel noise, baseline wander noise, muscle artefacts, electrode motion, often embedded with ECG signal. In this paper a methology to overcome from channel noise embedded during the transportation of ECG signal, proposed in this methodology DFT of noisy ECG signal calculated using fast fourier transform (FFT) algorithm. The experimental resultdemonstrate the proposed method is superior to other with higher SNR and lower RMSE factor, performance comparison at 1.25 dB is demonstrated.

© 2016 Elixir All rights reserved.

### Introduction

Tele:

ECG Electrocardiography is a technique which maps electrical activity of heart at the graph paper it is a non-invasive technique. In this technique several electrode placed on the skin at specific point on the body. Since the electrical activity is directly correlated to heart functioning. It can be used to inspect the regularities and rate of heart rhythms. Therefore any change in heart rhythm caused by cardiac rhythms will reflect in the person ECG also during acquisition and transmission, ECG signal are generally affected by different noises such as Gaussian noise in channel, baseline wander, muscle artefacts and electrode motion.

Muscle artefacts caused by the muscle activity and electrode motion due to the shifting of electrode location. Baseline wander is the variation in the isoelectric line of ECG which can occur during respiration. Poor channel condition is also caused noise in the ECG signal during its transmission. This noise corrupts the signal and makes the analysis time. Hence noisy ECG signal must be enhanced by removing the noise component at the time of processing.

There are various techniques in the literature for enhancements of ECG signal same of wavelet denoising, Stransform and many more. Most of these techniques concentrated only on kind of noise type. In this paper a new method for ECG signal enhancement using fast fourier transform effecting to overcome the channel noise limitation. During acquition of ECG signal the channel noise added while signal is transported. This paper proposed a generalised approach for ECG signal enhancement techniques and does not require any prior information like R peak position or references position. FFT is closely related to the DFT and SFT (Short Fourier Transformation)the proposed algorithm is evaluated for white Gaussian noise by means of SNR (Signal Noise Ratio ) and RMSE (Route Means Square ) error and experimental result shown that the proposed method result better performance compare to commonly use wavelet transform and S-transform. The performance of different ECG enhancement technique at 1.25dB input SNR and RMSE also compared.

# FFT (Fast Fourier Transform)

The fast fourier transform (FFT) is an algorithm that efficiently compute the discrete fourier transform (DFT). The DFT of a sequence  $\{x \ (n)\}$  of length N is given by a complex-valued sequence  $\{X \ (k)\}$ 

X (k) = 
$$\sum_{n=0}^{N-1} x(n) e^{-j2\pi nk/N}$$
,  $0 \le k \le N-1$  (1)

Let  $W_n$  be the complex – valued phase factor, which is an  $N^{\text{th}}$  root of unity expressed by

$$W_n = e^{-j2\pi/N}$$
(2)

Hence X (k) becomes  
X (k) = 
$$\sum_{n=0}^{N-1} x(n) W_N^{nk}$$
,  $0 \le k \le N-1$  (3)

Similarly IDFT becomes

$$x(n) = \frac{1}{N} \sum_{k=0}^{N-1} X(k) W_N^{-nk} , 0 \le n \le N-1$$
(4)

An efficient algorithm for DFT computation is the fast Fourier transform algorithm because exploit the two property symmetry and periodicity property.

Symmetry property 
$$W_N^{k+N/2} = -W_N^k$$
 (5)  
Periodicity  $W_N^{k+N} = W_N^k$  (6)

It is evident from the equ.(1), (2) and (3) for each value of k , the direct computation of X(k) involves N complex multiplication (4N real multiplication) and N-1 complex additions (4N-2 real additions). Therefore to compute all N values of DFT, N<sup>2</sup> complex multiplications and N (N-1) complex additions are required.

### Methodology

The enhancement of ECG signal throw FFT it can we achieved with the help of proposed methodology show the fig. (1).



Fig 1. Block diaram of ECG enhancement techenique

E-mail addresses: verma6226@gmail.com

© 2016 Elixir All rights reserved

Step 1 : Using FFT algorithm DFT of discrete noisy ECG h(n) sampled into n point and discrete noisy ECG signal h(n).

Using FFT algorithm DFT of discrete ECG signal h(n) ( N sample, at t=n ,h(t)=h(n) ) is defind as

X (k) = 
$$\sum_{n=0}^{N-1} h(n) W_N^{nk}$$
, 0 ≤ k ≤ N-1 (7)

X(k) is defind as how the amplitude changes over frequency. To obtain the noisy ECG signal for statical results. Time series h(t) is windowed (or multiplied point to point ) with window function (Gaussion function) g(t) then resulting spectrum is

$$H(f) = \int_{-\infty}^{\infty} h(t) e^{-i2\pi f t} dt$$
(8)
Concerning Gaussian function

Genearrlied Gaussaion function

$$g(t) = \frac{1}{\sigma\sqrt{2\pi}}e^{\frac{-t^2}{2\sigma^2}}$$
(9)

taking window width  $\sigma$  to proportion to inverse of frequency

$$\boldsymbol{\sigma}(\mathbf{f}) = \frac{1}{|f|} \tag{10}$$

DFT of noisy ECG signal h[kT] is given by

X [k, 
$$\frac{m}{NT}$$
] =  $\sum_{n=0}^{N-1} H[\frac{K+m}{NT}] e^{\frac{-2\pi^2 m^2}{n^2}} e^{\frac{i2\pi mj}{N}}$  (11)

Where H  $\left[\frac{m}{HT}\right]$  is fourier transform of frequency domain noisy ECG signal shown in fig.2 (a) is h[kT] with 154 selected frequency at 1.25 dB SNR level.



**Fig 2 (a) Noisy ECG signal (b) Reconstructed ECG signal** Step 2 : Appling frequency domain thresholding high frequency noise removed because ECG signal concentrated between band 0.05 - 100 Hz frequency. Therefore frequency below 200 Hz retain by frequency thresholding.

Step 3 : Masking and Filtering is done to remove noise between QRS complex of frequency domain by staticaly appropriate thresold.

Step 4: Taking IFFT of the filterd signal of step 3, reconstructed time domain ECG signal obtain and show in fig.2 (b).



Fig 3 (a) standard ECG signal available at MIT-BIH online database (b) noisy ECG signal (c) Reconstructed ECG signal using FFT

Fig. 3 (a), (b) and (c) shows the experimental result in which fig3. (a) is the standard ECG signal fig3.(b) is the noisy ECG signal .noise added to selected region marked in the graph .for the section of 0.5 Mhz and fig3.(c) shows the reconstructed signal of ECG after denoising through proposed methodology.

Standard signal and noisy signal show in fig.3 (a) and fig.3 (b) available at online MIT-BIH Arrhythmia database .This data base contains 48 ECG signal 30 min. duration which sampled at 360 Hz, an artificial noise is added to this signal that results 0dB, 1.25dB and .5dB SNR proposed methodology is to test denoising these noise signal and compared with other commonly used denoising method of ECG signal.

In this paper a artificial white Gaussian noise added to the standard ECG signal shown in fig3 (b) and it is represented the channel noise in the ECG signal while transporting ,for the duration of 0.5 Mhz frequency shown in fig 3 (b) by dotted spectrum .The channel noise introduced into the signal due to the poor channel condition and same can be modelled by white Gaussian noise which all frequency components, after adding artificial Gaussian noise at 1.25dB, a portion of distorted signal in the duration 0.5 MHz.

The proposed method reconstructs the signal and check the accuracy by two factor SNR and RMSE from the result obtain the help of MATLAB version (7.9.0.529) at window 7 platform. The proposed method gives better performance with higher SNR of 12.07dB and lower RMSE is 0.269, the reconstructed signal shown in the fig 3 (c).

### Performance comparison with WT and S-transform Table 1. comparison of SNR and RMSE of various

techniques			
MIT-BIH	WT	S transform	FFT
Tape no.103	** 1	5-transform	TTT
SNR	6.72	10.95	12.07
RMSE	0.461	0.284	0.269

Table no 1 shows that comparison between various techniques wavelet transform , S-transform , and proposed method (FFT) ,result shows that the higher SNR (12.07dB) and lower RMSE (0.269dB) which is desirable for any signal therefore proposed method(FFT) Fast Fourier transform is more suitable than any other commonly used method .

# **Conclusion and future aspect**

It can be concluded from experimental result and variance (ANOVA) based statistical method, proposed FFT algorithm based DFT method of enhancement of channel noise embedded with ECG signal shows better performance. Showing higher SNR and low RMSE from generally used techniques used to ECG signal enhancement .ECG signal required to accurate analysis of heart condition therefore proposed method may play vital role in analysis of ECG signal and diagnosis of heart diseases.

### Reference

• Samit Ari, Manab Kumar Das, Anil Chacko, ECG signal enhancement using S-Transform ,Elsevier, Computer in Biology And Science 43(2013) 649-660.

• S Salivahanan, A Vallavaraj, C Gnanapriya, Digital Signal Processing, Tata Mc Graw Hill Edu.Pvt.Ltd., 2010.

• R.Rangayyan, Biomedical Signal Analysis: A Case –study approach, Wiley India Pvt. Ltd. 2009.

• O.Sayadi, M.B.Shamsollahi, ECG denoising and compression using a modified extended kalman filter structure,IEEE Trans.Biomed.Eng.55 (September (9)) (2008) 2240-2248. • M.Blanco-Velasco, B.Weng, K.E.Barner, ECG Signal denoising and baseline wander correction based on the empirical mode decomposition, Comput.Biol.Med. 38 (1) (2008) 1-13.

• A.K.Barros, A. Mansour, N. Ohnishi, Removing artifacts from electrocardiographic signals using independent components analysis, Neurocomputing 22 (13) (1998) 173-186.

• E.Ercelebi, Electrocardiogram signals de-noising using liftingbased discrete wavelet transform, Comput. Bio. Med. 34 (6) (2004) 479-493.

• S. Poornachandra, Wavelet-based denoising using subband dependent threshold for ECG signals, Digital Signal Process. 18 (1) (2008) 49-55.

• J.S.Paul,M.,R.Reddy,V.J.Kumar, A Transform domain SVD filterfor soppresion of muscle noise artifacts in excersise ECG, IEEE Trans. Biomed. Eng.55 (January (1)) (2008) 347-351.

• B.Acar, H. Koymen, SVD- based on-line exercise ECG signal orthogonalization IEEE Trans.Biomed. Eng.46 (March (3)) (1999) 311-321.

• T.Y. Ji, Z. Lu, Q.H. Wu, Z.Ji, Baseline normalisation of ECG signals using empirical mode decomposition and mathematical morphology, Electron. Lett. 44 (2) (2008) 82-83.

• R.G.Stockwell, Why use the S-Transform? In: Wong (ed.), pseudo- differencial operators; PDEs and Time-frequency analysis, ser.feilds institute communications AMS, vol. 52, 2007, 279-309.

• R. G. Stockwell, A basis for efficient representation of the S-transform, digital signal processing17 (1), 2007, 371-393

• MIT-BIH arrhythmia database. [Online]. Available: http://www.physionet.org/physiobank/database/mitdb/.

• The MIT-BIH noise stress test database. [Online]. Available: < www.physionet.org/physibank/database/nstdb/>

• P. W. Macfarlane and T. D. W. Lawrie, eds., Comprehensive Electrocardiology. Theory and Practice in Health and Disease, vols. 1, 2, 3. New York: Pergamon Press, 1989.

• J. J. Bailey, A. S. Berson, A. Garson, L. G. Horan, P. W. Macfarlanc, D. W. Mortara, and C. Zywictz, Recommendations for the standardization and specifications in automated electrocardiography: bandwidth and signal processing. Circulation 1990; 81:730–739.

• T. Y. Young and W. H. Huggins, On the representation of electrocardiograms. IEEE Trans. Biomed. Eng. 1963; 10:86–95.



JITENDRA KUMAR VERMA is student of M.Tech. ECE(SP) in the Department of Electronics & Communication, Engineering in SHIATS- DU Allahabad. He received his B.Tech degree from Institute of Engineering & Technology Dr.R.M.L.Awadh University Faizabad U.P. INDIA



Dr. Anil Kumar is Assistant Professor in ECE Department at SHIATS-DU Allahabad. He obtained B.E from MMMEC Gorakhpur in ECE, M.Tech. from IIT BHU Formerly IT B.H.U. Varanasi in Microelectronics Engg. And he has done Ph.D. from SHIATS-DU Allahabad. He guided various projects & research at undergraduate & postgraduate level. He published many research papers in different journals. He has more than 10 years teaching experience and actively involved in research and publications. His area of interest includes Antenna, microwave, artificial neural network and VLSI.



Prof. A.K. Jaiswal is Prof. and Head of ECE-Department at SHIATS Allahabad. He obtained M.Sc. in Tech. Electronics & Radio Engg. from Allahabad University in 1967. He guided various projects & research at undergraduate & postgraduate level. He has more than 40 years Industrial, research and Teaching experience and actively involved in research and publications. His area of interest includes Optical Networks and satellite communication.